

## MULTI CORE CABLE COLOUR CODE

### PAIR COLOURS:

1 B/B-W	36 B-W/BK-W	71 R-B/R-V
2 O/O-W	37 O-W/BK-W	72 R-O/R-V
3 G/G-W	38 G-W/BK-W	73 R-B/R-V
4 BN/BN-W	39 BN-W/BK-W	74 R-BN/R-V
5 S/S-W	40 S-W/BK-W	75 R-S/R-V
6 B/B-R	41 B-W/Y-W	76 B-BK/BK-W
7 O/O-R	42 O-W/Y-W	77 O-BK/BK-W
8 G/G-R	43 G-W/Y-W	78 B-BK/BK-W
9 BN/BN-R	44 BN-W/Y-W	79 BN-BK/BK-W
10 S/S-R	45 S-W/Y-W	80 S-BK/BK-W
11 B/B-BK	46 B-W/V-W	81 B-BK/R-BK
12 O/O-BK	47 O-W/V-W	82 O-BK/R-BK
13 G/G-BK	48 G-W/V-W	83 G-BK/R-BK
14 BN/BN-BK	49 BN-W/V-W	84 BN-BK/R-BK
15 S/S-BK	50 S-W/V-W	85 S-BK/R-BK
16 B/B-Y	51 R-B/R-W	86 B-BK/BK
17 O/O-Y	52 R-O/R-W	87 O-BK/BK
18 G/G-Y	53 R-G/R-W	88 G-BK/BK
19 BN/BN-Y	54 R-BW/R-W	89 BN-BK/BK
20 S/S-Y	55 R-S/R-W	90 S-BK/BK
21 B/B-V	56 R-B/R	91 B-BK/BK-Y
22 O/O-V	57 R-O/R	92 O-BK/BK-Y
23 G/G-V	58 R-G/R	93 G-BK/BK-Y
24 BN/BN-V	59 R-BN/R	94 BN-BK/BK-Y
25 S/S-V	60 R-S/R	95 S-BK/BK-Y
26 B-W/W	61 R-B/R-BK	96 B-BK/BK-V
27 O-W/W	62 R-O/R-BK	97 O-BK/BK-V
28 G-W/W	63 R-G/R-BK	98 G-BK/BK-V
29 BN-W/W	64 R-BN/R-BK	99 BN-BK/BK-V
30 S-W/W	65 R-S/R-BK	100 S-BK/BK-V
31 B-W/R-W	66 R-B/R-Y	
32 O-W/R-W	67 R-O/R-Y	
33 G-W/R-W	68 R-G/R-Y	
34 BN-W/R-W	69 R-BN/R-Y	
35 S-W/R-W	70 R-S/R-Y	

### KEY:

B = BLUE  
 BK = BLACK  
 BN = BROWN  
 G = GREEN  
 O = ORANGE  
 W = WHITE

### PAIR COLOURS:

1: BLUE/WHITE	6: BLUE/RED
2: ORANGE/WHITE	7: ORANGE/RED
3: GREEN/WHITE	8: GREEN/RED
4: BROWN/WHITE	9: BROWN/RED
5: SLATE/WHITE	10: SLATE/RED